



#### Basic features

Application	Object detection
Approval/Conformity	CE cULus WEEE UKCA
Basic standard	IEC 60947-5-2
Scope of delivery	2x nut M12x1

#### Display/Operation

Function indicator	yes
Power indicator	yes

#### Electrical connection

Connection	M12x1-Male, 3-pin, A-coded
Electrical version	3-wire
Polarity reversal protected	yes
Protection against device mix-ups	yes
Short-circuit protection	yes

#### Electrical data

Load capacitance max. at Ue	1 $\mu$ F
Min. operating current Im	0 mA
No-load current Io max., damped	8.5 mA
No-load current Io max., undamped	5 mA
Operating voltage Ub	10...30 VDC
Output resistance Ra	Open drain
Rated insulation voltage Ui	75 V DC
Rated operating current Ie	100 mA
Rated operating voltage Ue DC	24 V
Rated short circuit current	100 A
Ready delay tv max.	50 ms
Ripple max. (% of Ue)	15 %
Switching frequency	350 Hz
Utilization category	DC -13
Voltage drop static max.	1.3 V

#### Environmental conditions

Ambient temperature	-25...70 °C
Contamination scale	3
EN 60068-2-27, Shock	Half-sinus, 30 gn, 11 ms
EN 60068-2-6, Vibration	55 Hz, amplitude 1 mm, 3x30 min
IP rating	IP67

#### Functional safety

MTTF (40 °C)	1410 a
--------------	--------

#### Interface

Switching output	PNP normally open (NO)
------------------	------------------------

Inductive Sensors  
BES M12ZI-PSC40B-S04G  
Order Code: BES060U

**BALLUFF**

Material

Housing material	Die-cast zinc, nickel-plated PC
Material sensing surface	PBT

Mechanical data

Dimension	Ø 12 x 65 mm
Installation	for flush mounting
Mounting length	49 mm
Size	M12x1
Tightening torque max.	6 Nm

Range/Distance

Assured operating distance Sa	3.2 mm
Hysteresis H max. (% of Sr)	15 %
Rated operating distance Sn	4 mm
Repeat accuracy max. (% of Sr)	5 %
Switching distance marking	■ ■
Temperature drift max. (% of Sr)	10 %
Tolerance Sr	10 %

Remarks

The sensor is functional again after the overload has been eliminated.  
Find the installation instructions for inductive sensors in the download area of the sensor on the homepage.  
The given values are typical values and might differ at the operational limits of the sensor (temperatur < -10°C) and under application specific conditions.  
Status LED:  
Off: No supply voltage or sensor defective  
Green: Sensor ready, supply voltage applied  
Yellow: Target detected  
Red: Error detected: short circuit  
undervoltage < 5-8 VDC  
overtemperature or overload  
Error condition is only displayed in damped state  
For more information about MTTF and B10d see MTTF / B10d Certificate

Indication of the MTTF- / B10d value does not represent a binding composition and/or life expectancy assurance; these are simply experiential values with no warranty implications. These declared values also do not extend the expiration period for defect claims or affect it in any way.

Connector Drawings



Wiring Diagrams (Schematic)

