



FS-T0

Fiber Amplifier, Zero-line Expansion Unit



*Please note that accessories depicted in the image are for illustrative purposes only and may not be included with the product.

! This model has been discontinued.
Compliance with the certification standard is ensured as of the time of shipment from our company.

Contact Us: 1-888-539-3623

Recommended Replaceable Products: [Digital Fiber Optic Sensor - FS-N40 series](#)

Specifications

Model		FS-T0
Type		0-line expansion unit
Output		-
Light source		Red LED
Sensitivity adjustment/Mode selection		Button
Response time		410 μs to 1 ms*1
Operation mode		LIGHT-ON/DARK-ON (switch-selectable)
Indicator lamp		Output indicator: Red LED, Stable operation indicator: Green LED Calibration indicator: Orange LED
Timer function		ON-delay: 40 ms/OFF-delay: 40 ms/Timer OFF (switch-selectable)
Input		Non-voltage input (contact, solid state)
Control output		—
Stability output		
Protection circuit		Reversed polarity protection, over-current protection, surge absorber
Unit expansion		Up to 16 expansion units can be connected (a total of 17 units).*2
Mutual interference suppression		FINE : 4, TURBO/SUPER: 8
Rating	Power voltage	12 to 24 VDC ±10 %, Ripple (P-P) 10 % or less*3
	Current consumption	35 mA or less
Environmental resistance	Ambient light	Incandescent lamp: 10,000 lux max., Sunlight: 20,000 lux max.
	Ambient temperature	-10 to +55 °C 14 to 131 °F (No freezing)*4
	Relative humidity	35 to 85 % RH (No condensation)
	Vibration resistance	10 to 55 Hz, Double amplitude 1.5 mm 0.06", 2 hours in each of the X, Y, and Z directions
	Shock resistance	500 m/s², 3 times in each of the X, Y, and Z directions
Case material		Polycarbonate
Weight		Approx. 20 g

^{*1} The response speed varies depending on the number of expansion units connected.

^{*2} If more than one unit is used together, the ambient temperature varies with the conditions below. Mount the units on the DIN rail with mounting brackets and check that the output current is 20 mA or less.

3 to 10 Units: -10 to 50°C **14 to 122°F**, 11 to 16 Units: -10 to 45°C **14 to 113°F**

^{*3} Power to the FS-T2/M2 is supplied through the FS-T1/M1/V1/V11/, PS-T1, LV-21A/11A.

*4 When several units are connected, the ambient temperature requirement varies depending on the total number of units connected.

When 3 to 10 units: -10 to +50 °C 14 to 122 °F

When 11 to 16 units: -10 to +45 °C 14 to 113 °F

When connecting several units, be sure to mount the units to a metallic DIN rail. Make sure that the output current does not exceed 20 mA.

Dimensions

* Download CAD file or product manual for larger image/text and more detail.

