



KV-N40DT

Base Unit, DC power supply type, Input 24 points/output 16 points, transistor (sink) output



*Please note that accessories depicted in the image are for illustrative purposes only and may not be included with the product.

Specifications

Model			KV-N40DT
General specifications	Power voltage		24 VDC (+10%/-15%)
	Operating ambient temperature		0 to 55°C 32 to 131°F (no freezing)*1 *2
	Operating ambient humidity		5 to 95% RH (no condensation)*1
	Operating environment		As little dust and corrosive gas as possible
	Noise immunity		1500 V peak-to-peak or more, pulse duration 1 µs, 50 ns (based on noise simulator), IEC standard compliant (IEC61000-4-2/3/4/6)
	Withstand voltage		1500 VAC for 1 minute, between power supply terminal and I/O terminals and between all external terminals and case
	Insulation resistance		50 MΩ or more (500 VDC megger used to perform measurements between power terminal and input terminals, and between all external terminals and case)
	Output power supply voltage		–
	Storage temperature		–25 to +75°C –13 to +167°F
	Vibration resistance	Intermittent vibration	Frequency: 5 to 9 Hz Amplitude: 3.5 mm 0.14"/s² *3*4
			Frequency: 9 to 150 Hz Acceleration: 9.8 m/s ² 32.2"/s² *3*4
		Continuous vibration	Frequency: 5 to 9 Hz Amplitude: 1.75 mm 0.07"/s² *3*4
			Frequency: 9 to 150 Hz Acceleration: 4.9 m/s ² 16.1"/s² *3*4
Performance specifications	Shock resistance		Acceleration: 150 m/s ² 492.1"/s² , application time: 11 ms, three times in each of the X, Y, and Z directions
	Operating altitude		2000 m 6561.7' or less
	Overvoltage category		AC: II, DC: I
	Pollution degree		2
	Calculation control method		Program storage method
	I/O control method		Refresh method
	Program language		Expanded ladder, KV Script, mnemonic
	Number of instructions		Basic instruction: 81 types and 182 instructions, Application instruction: 39 types and 56 instructions Calculation instruction: 123 types and 311 instructions, Expansion instruction: 92 types and 141 instructions, Total: 335 types and 690 instructions
	Instruction execution speed		Basic instruction: 50 ns minimum, Application instruction: 170 ns minimum
	Program capacity		16k steps
	Maximum number of attachable I/O units		8
	Maximum number of I/O points		256 (excluding the base unit I/O)
	Input relay/ Output relay/	R	Total of 9600 points 1 bit (R000 to R59915)

Internal auxiliary relay		
Link relay	B	8192 points 1 bit (B0 to B1FFF)
Internal auxiliary relay	MR	9600 points 1 bit (MR000 to MR59915)
Latch relay	LR	3200 points 1 bit (LR000 to LR19915)
Control relay	CR	1440 points 1 bit (CR000 to CR8915)
Timer	T	512 points 32 bit (T0 to T511)
Counter	C	256 points 32 bit (C0 to C255)
Data memory	DM	32768 points 16 bit (DM0 to DM32767)
Link register	W	16384 points 16 bit (W0 to W3FFF)
Temporary memory	TM	512 points 16 bit (TM0 to TM511)
High-speed counter	CTH	3 points (CTH0 to CTH2), 32-bit automatic reset counter ^{*5} (Input response: 100 kHz per single phase, 50 kHz per phase difference) ^{*6}
High-speed counter comparator	CTC	6 points (CTC0 to CTC5), 32 bits, two points per high-speed counter
Index register	Z	12 points 32 bit (Z01 to Z12)
Control memory	CM	9000 points 16 bit (CM0 to CM8999)
Positioning pulse output		3 axes, Maximum output frequency: 100 kHz
Base unit I/O		Input: 24 points, output: 16 points, Input common: 1 point, Output common: 2 points
Number of comments and labels that can be stored in the main unit	Device comment	20000 When a maximum-length ladder program is written with no labels.
	Label	28000 When a maximum-length ladder program is written with no device comments.
Power off hold function	Program memory	Flash ROM can be rewritten 10000 times
	Device	Nonvolatile RAM ^{*7}
Self-diagnosis function		CPU error, RAM error, and other problems
Input specifications	Relay number	General input: R000 to R007, R014 to R107 (18 points) High-speed A-phase and B-phase input: R008 to R013 (3 channels, 6 points in total)
	Input mode	24 VDC input (open collector)
	Maximum input voltage	26.4 VDC
	Rated input voltage	24 VDC (General input: 5.3 mA, High-speed A-phase and B-phase input: 6.5 mA ^{*8})
	Minimum ON voltage	19 VDC
	Maximum OFF current	1.5 mA
	Common method	General input: All points/1 common (1 terminal), High-speed A-phase and B-phase input: Shared common for all points (shared with general input)
	Circuit delay time	General input: OFF to ON: Max. 30 µs (Typ. 3.5 µs), ON to OFF: Max. 50 µs (Typ. 15 µs) High-speed A-phase and B-phase input: OFF to ON: Max. 2 µs (Typ. 1.1 µs), ON to OFF: Max. 2 µs (Typ. 0.3 µs) *9
	Input time constant	Normal: 10 ms, When the HSP instruction is used: 10 µs When CR2305 is turned ON: 10 µs to 10 ms, eight-level switching is possible (set with CM1620). Can also be set from the Unit Editor.*9 Input time constant setting 10 µs: Digital filter 1.6 to 2 µs Input time constant setting 20 µs: Digital filter 9 to 12 µs Input time constant setting 110 µs: Digital filter 90 to 93 µs Input time constant setting 500 µs: Digital filter 300 to 400 µs Input time constant setting 1 ms: Digital filter 800 to 900 µs Input time constant setting 2.5 ms: Digital filter 2.3 to 2.4 ms

		Input time constant setting 5 ms: Digital filter 4.0 to 4.5 ms Input time constant setting 10 ms: Digital filter 9 to 9.5 ms
	Response frequency	(High-speed A-phase and B-phase input) Single phase: 100 kHz, phase difference: 50 kHz, 24 V ±10%, Duty 50%
Output specifications	Relay number	General output: R506 to R515 (10 points), High-speed output: R500 to R505 (6 points)
	Output mode	MOSFET *10
	Rated load	30 VDC, 0.5 A
	Maximum OFF voltage	30 VDC
	Leakage current at OFF	100 µA or less
	Residual voltage at ON	0.8 VDC or less (with 0.5 A output), 0.6 VDC or less (with 0.3 A output)
	Common method	8 to 10 points/1 common
	ON/OFF response time	General output: OFF to ON: 100 µs (load of 1 mA or more), ON to OFF: 200 µs (load of 1 mA or more) High-speed output: OFF to ON: 2 µs (7 to 100 mA load), ON to OFF: 5 µs (7 to 100 mA load)
	Overcurrent protection	Protection provided for each common*11
	Output frequency	High-speed output: 100 kHz (7 to 100 mA load)
Built-in serial port	Interface	Communication standard RS-232C
		Connection Modular connector
	Transmission specifications RS-232C	Baud rate 1200, 2400, 4800, 9600, 19200, 38400, 57600, 115200 bps
		Transmission method Full duplex
		Data format Start bit 1 bit
		Data bits 7 bits, 8 bits
		Stop bits 1 bit, 2 bits
		Error detection Parity Even, odd, none
		Transmission distance 15 m 49.2'
		Number of transmission units 1
	Indication	SD (green), RD (red)
Internal current consumption		250 mA
Weight		Approx. 530 g

*1 The range guaranteed as a system (excluding items specially noted for the units and cassettes).

*2 The temperature below the unit center (30 mm **1.18"**) inside a control panel.

*3 These specifications correspond to situations in which the unit is mounted on a DIN rail and in which the unit is mounted on the panel directly.

*4 Conforms to JIS B 3502 and IEC61131-2, Scan times: 10 times (100 minutes) in each of the X, Y, and Z directions

*5 You can also configure the settings so that automatic reset is not used.

*6 Only open collectors are supported. Line drivers are not supported.

*7 You can set the target device by clicking "CPU system setting" and then "Power off holding" in KV STUDIO.

*8 Reference value of input current.

*9 The input response time corresponding to the input time constant can be calculated as shown below. (Response time) = (Circuit delay of the input circuit) + (Delay by the digital filter)

Example: Maximum response time when the input time constant is set to 500 µs

OFF to ON: 30 µs (circuit delay) + 400 µs (digital filter) = 430 µs

ON to OFF: 50 µs (circuit delay) + 400 µs (digital filter) = 450 µs

*10 MOSFET (N-ch) output for the sink output type.

*11 If an overcurrent occurs, the protection operation (output turned OFF) and automatic recovery are repeated for all outputs within the shared common until the cause of the problem is removed.

Dimensions

* Download CAD file or product manual for larger image/text and more detail.

KV-N40DR/N40DT(P)

