



## **KV-B16TCP**

16-point Screw Terminal Block, Transistor (Source)





\*Please note that accessories depicted in the image are for illustrative purposes only and may not be included with the product.

## **Specifications**

| Model                        |                        | KV-B16TCP  |
|------------------------------|------------------------|--|
| Туре                         |                        | Output unit  |
| External connection method   |                        | Removable terminal block                           |
| Output                       | Number of outputs      | 16 points  |
|                              | Output mode            | Transistor (source)                                |
|                              | Rated load             | 30 VDC, 0.2 A                                      |
|                              | Leakage current at OFF | 100 μA or less                                     |
|                              | Residual voltage at ON | 0.5 V or less                                      |
|                              | ON resistance          | -  |
|                              | Common method          | 16 points/1 common (2 terminals)*1                 |
|                              | Operation time         | OFF to ON: 10 μs or less,ON to OFF: 200 μs or less |
| Internal current consumption |                        | 30 mA or less                                      |
| Weight                       |                        | Approx. 130 g                                      |

<sup>\*1</sup> Although KV-B16TD, KV-C32TD, KV-B16TCP, and KV-C32TCP have two points, they are the same internally.



## **Dimensions**

\* Download CAD file or product manual for larger image/text and more detail.

KV-B16TCP



