




KV-E8T

8-output Transistor (Sink)



*Please note that accessories depicted in the image are for illustrative purposes only and may not be included with the product.

! This model has been discontinued.

Contact Us: 1-888-539-3623

Compliance with the certification standard is ensured as of the time of shipment from our company.

Recommended Replaceable Products: [Expansion output unit output 8 points transistor \(sink\) output screw terminal block - KV-N8ET](#)

Specifications

Model	KV-E8T	
Number of outputs	8	
Output	Transistor (NPN) ^{*1}	
Rated load voltage	30 VDC	
Rated output current	0.5 A/output	
Leakage current (at OFF)	100 µA or less	
Residual voltage (at ON)	0.8 V or less	
Startup operation time (OFF → ON)	50 µs or less	
Startup operation time (ON → OFF)	250 µs or less	
ON resistance	—	
Relay life span		
Relay replacement		
General specifications	Weight	Approx 100g
Output specifications	Common output	COM is shared internally.
	External connection method	Terminal block

^{*1} Contact KEYENCE for information on the PNP output type.

Dimensions

* Download CAD file or product manual for larger image/text and more detail.

Kv-e8

