



KV-N8ER

Expansion output unit, output 8 points, relay output, screw terminal block



*Please note that accessories depicted in the image are for illustrative purposes only and may not be included with the product.

Specifications

| | | | |
|------------------------------|--------------------------------------|---------------|---|
| Model | | KV-N8ER | |
| Expansion output unit | Output Points | | 8 points |
| | External connectionmethod | | Relay |
| | External connection method | | Terminal block |
| | Rated load | | 250 VAC/30 VDC, 2 A |
| | Leakage current (when output is OFF) | | – |
| | Residual voltage (at ON) | | |
| | ON resistance | | 50 mΩ or less |
| | Common method | | Independent |
| | Response time | OFF to ON | 10 ms or less |
| | | ON to OFF | |
| | Relay life | | Electrical: 100000 cycles or more (20 cycles/minute) Mechanical: 20000000 cycles or more |
| | Relay replacement | | Impossible |
| Internal current consumption | | 60 mA or less | |
| Weight | | Approx. 230 g | |

Dimensions

* Download CAD file or product manual for larger image/text and more detail.

KV-N8ER

