



LZ-A152

Amplifier Unit

*Please note that accessories depicted in the image are for illustrative purposes only and may not be included with the product.

ⓘ

This model has been discontinued.

Compliance with the certification standard is ensured as of the time of shipment from our company.

Contact Us: 1-888-539-3623

Recommended Replaceable Products: [Multi-Purpose Digital Laser Sensor - LV-N series](#)

Specifications

Model		LZ-A152
Sensitivity adjustment		Many-turn trimmer (7 turns)
Output status		Switchable by way of a switch (LIGHT ON <=> DARK ON)
Response time		—
		2.5ms or less
Power on reset		1s or less
Indicator lamp		Operation: red LED
Control output		NPN open-collector 100 mA max. (40 V max.)
Rating	Power voltage	12 to 24 VDC ±10 %, Ripple (P-P)
	Current consumption	60 mA or less
Environmental resistance	Ambient temperature	0 to +50 °C 32 to 122 °F
	Relative humidity	35 to 85 % RH
Weight		Approx. 75 g (including the cable)

Dimensions

* Download CAD file or product manual for larger image/text and more detail.

